

## Z-Wave Protocol Implementation Conformance Statement

# In-Wall Smart Motion Dimmer

### General Information

<b>Product Identifier:</b>	26932
<b>Brand Name:</b>	Jasco Products Company
<b>Product Version:</b>	HW: 255 FW: 5.50
<b>Z-Wave Certification #:</b>	ZC10-16125335

### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Neutral Wire Required</b>	Yes
<b>Sensors</b>	Motion/No Motion (Binary)

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3033
<b>Z-Wave Product Type:</b>	0x494D
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.08
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

### Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall Smart Motion Dimmer

2 / 5 Supports Basic Set and is controlled by pressing On/Off button with local load

3 / 5 Supports Basic Set and is controlled by pressing On/Off button with local load

### Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
CRC16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Notification V4	Powerlevel
Scene Activation	Scene Actuator Conf
Switch All	Switch Multilevel V2
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic