

Z-Wave Protocol Implementation Conformance Statement

Z-Weather

General Information

Product Identifier:	POPE005206
Brand Name:	Popp
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-16125341

Product Features

Color	Black
Outdoor Use	Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0400
Z-Wave Product Type:	0x0100
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Z-Wave Plus Lifeline
2 / 5	Too windy. If the threshold value for wind (Default value: 6m/s) is exceeded, the basic set is sent to all group

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Weather

- 3 / 5 It is getting bright. Sends BASIC SET command in the morning when brightness reached trigger level (Default value: 37%)
- 4 / 5 It is getting dark. Sends BASIC SET command in the evening when brightness reached trigger level (Default value: 37%)

Supported Command Classes (17):

- | | |
|-----------------------------------|------------------------|
| Association Command Configuration | Association Group Info |
| Association V2 | Basic |
| Battery | Configuration V2 |
| Device Reset Locally | Language |
| Manufacturer Specific V2 | Meter V3 |
| Multi Channel Association V2 | Multi-Command |
| Powerlevel | Sensor Multilevel V6 |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (2):

- | | |
|-------|---------------|
| Basic | Multi-Command |
|-------|---------------|