

## Z-Wave Protocol Implementation Conformance Statement

### Z-Weather

#### General Information

<b>Product Identifier:</b>	POPE005206
<b>Brand Name:</b>	Popp
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-16125341

#### Product Features

<b>Color</b>	Black
<b>Outdoor Use</b>	Yes

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0400
<b>Z-Wave Product Type:</b>	0x0100
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 5	Z-Wave Plus Lifeline
2 / 5	Too windy. If the threshold value for wind (Default value: 6m/s ) is exceeded, the basic set is sent to all group

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Weather

- 3 / 5 It is getting bright. Sends BASIC SET command in the morning when brightness reached trigger level (Default value: 37%)
- 4 / 5 It is getting dark. Sends BASIC SET command in the evening when brightness reached trigger level (Default value: 37%)

### Supported Command Classes (17):

- |                                   |                        |
|-----------------------------------|------------------------|
| Association Command Configuration | Association Group Info |
| Association V2                    | Basic                  |
| Battery                           | Configuration V2       |
| Device Reset Locally              | Language               |
| Manufacturer Specific V2          | Meter V3               |
| Multi Channel Association V2      | Multi-Command          |
| Powerlevel                        | Sensor Multilevel V6   |
| Version V2                        | Wake Up V2             |
| Z-Wave Plus Info V2               |                        |

### Controlled Command Classes (2):

- |       |               |
|-------|---------------|
| Basic | Multi-Command |
|-------|---------------|