

## Z-Wave Protocol Implementation Conformance Statement

# Smoke Detector and Siren

### General Information

<b>Product Identifier:</b>	POPE004001
<b>Brand Name:</b>	Popp
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-16125371

### Product Features

<b>Battery Quantity</b>	1
<b>Battery Type</b>	9V Block
<b>Color</b>	White

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0201
<b>Z-Wave Product Type:</b>	0x0100
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Listening Sleeping Slave

### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smoke Detector and Siren

- 2 / 4 Alarm Reports
- 3 / 4 Switch Command when Alarm

### Supported Command Classes (15):

Association Group Info	Association V2
Basic	Battery
Configuration	Device Reset Locally
Firmware Update Meta-Data V3	Manufacturer Specific
Notification V5	Powerlevel
Security S0	Sensor Binary V2
Switch Binary	Version V2
Z-Wave Plus Info V2	

### Controlled Command Classes (3):

Basic	Notification V5
Security S0	