

## Z-Wave Protocol Implementation Conformance Statement

### SmartPlug-16A

#### General Information

<b>Product Identifier:</b>	SPD-02A
<b>Brand Name:</b>	LG Uplus
<b>Product Version:</b>	HW: 17 FW: 0.01
<b>Z-Wave Certification #:</b>	ZC10-17015386

#### Product Features

<b>Switch Load Capacity Volt-Ampere</b>	3600VA (220V)
<b>Switch Load Capacity Watts</b>	~3600W
<b>Switch Load Capacity Current</b>	16A
<b>Firmware Updatable</b>	Updatable by Manufacturer Representative
<b>Supported Meter Type</b>	Electric Energy
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	South Korea
<b>Z-Wave Product ID:</b>	0x0007
<b>Z-Wave Product Type:</b>	0x0042
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.61.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

SmartPlug-16A

## Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline, see attached manual.

**Supported Command Classes (13):**

Association Group Info	Association V2
Basic	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Meter V3	Notification V3
Powerlevel	Security S0
Switch Binary	Version V2
Z-Wave Plus Info V2	