



## Z-Wave Protocol Implementation Conformance Statement

### Zooz Z-Wave Plus Smart Chime

#### General Information

**Product Identifier:** ZSE33  
**Brand Name:** Zooz  
**Product Version:** HW: 48 FW: 2.65  
**Z-Wave Certification #:** ZC10-17015394

#### Product Features

**Battery Quantity** 2  
**Battery Type** CR123  
**Color** White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? No  
Supports Security S2? No  
SmartStart Compatible? No

#### Z-Wave Technical Information

**Z-Wave Frequency:** U.S. / Canada / Mexico  
**Z-Wave Product ID:** 0x0088  
**Z-Wave Product Type:** 0x0003  
**Z-Wave Hardware Platform:** ZM5202  
**Z-Wave Development Kit Version:** 6.51.08  
**Z-Wave Library Type:** Routing Slave  
**Z-Wave Device Type / Role Type:** Siren / Listening Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Zooz Z-Wave Plus Smart Chime

### Association Group Information

**Group # / Max    Description**

**Nodes**

- |       |  |
|-------|--|
| 1 / 5 | Z-Wave Plus Lifeline. Supported command classes: SWITCH_BINARY_REPORT NOTIFICATION_REPORT BATTERY_REPORT DEVICE_RESET_LOCALLY_NOTIFICATION |
| 2 / 5 | Status notifications to Z-Wave devices associated in this group. Supported command classes: SWITCH_BINARY_REPORT                           |
| 3 / 5 | Notifications to Z-Wave devices associated in this group. Supported command classes: NOTIFICATION_REPORT                                   |

**Supported Command Classes (12):**

- |  |                                    |
|--|------------------------------------|
| Command Class Association Group Info   | Command Class Association V2       |
| Command Class Basic                    | Command Class Battery              |
| Command Class Configuration            | Command Class Device Reset Locally |
| Command Class Manufacturer Specific V2 | Command Class Notification V6      |
| Command Class Powerlevel               | Command Class Switch Binary        |
| Command Class Version V2               | Command Class Z-Wave+ Info V2      |