

## Z-Wave Protocol Implementation Conformance Statement

### Zooz Z-Wave Plus Smart Chime

#### General Information

<b>Product Identifier:</b>	ZSE33
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 48 FW: 2.65
<b>Z-Wave Certification #:</b>	ZC10-17015394

#### Product Features

<b>Battery Quantity</b>	2
<b>Battery Type</b>	CR123
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0088
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.08
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	Siren / Listening Sleeping Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Zooz Z-Wave Plus Smart Chime

2 / 5            Status notifications to Z-Wave devices associated in this group. Supported command classes:  
SWITCH\_BINARY\_REPORT

3 / 5            Notifications to Z-Wave devices associated in this group. Supported command classes:  
NOTIFICATION\_REPORT

### Supported Command Classes (12):

Association Group Info  
Basic  
Configuration  
Manufacturer Specific V2  
Powerlevel  
Version V2

Association V2  
Battery  
Device Reset Locally  
Notification V6  
Switch Binary  
Z-Wave Plus Info V2