

## Z-Wave Protocol Implementation Conformance Statement

### Z-Wave Interface Module

#### General Information

<b>Product Identifier:</b>	ZW-9 (AU)
<b>Brand Name:</b>	Remote Technologies Incorporated
<b>Product Version:</b>	HW: 193 FW: 4.38:01.00
<b>Z-Wave Certification #:</b>	ZC10-17035478

#### Product Features

<b>IP (Ingress Protection) Rated</b>	No
<b>Outdoor Use</b>	No
<b>Color</b>	Black
<b>Communications Connections</b>	Ethernet (Wired)
<b>Communications Protocol</b>	Manufacturer Proprietary Protocol
<b>Controller Supports Multiple Networks</b>	No
<b>Controller Supports Multiple Z-Wave Interfaces</b>	No
<b>Firmware Updatable</b>	Updatable by Consumer by Wire

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Interface Module

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Australia / New Zealand
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5304
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Static Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway / Central Static Controller

### Association Group Information

**Group # / Max**    **Description**

#### Nodes

1 / 1                    Z-Wave Plus Lifeline

#### Supported Command Classes (10):

Application Status	Association Group Information V2
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific V2
Powerlevel	Security S0
Version V2	Z-Wave Plus Info V2

#### Controlled Command Classes (37):

Association Group Information V2	Association V2
Barrier Operator	Basic V2
Battery	Configuration V3
CRC16 Encapsulation	Door Lock V3
Indicator	Manufacturer Specific V2
Meter V4	Multi-Channel Association V3
Multi-Channel V4	Network Management Basic
Network Management Inclusion	Network Management Primary
Network Management Proxy	No Operation
Notification V3	Powerlevel
Scene Activation	Scene Actuator Conf
Scene Controller Conf	Security S0
Switch All	Switch Binary V2
Switch Multilevel V4	Thermostat Fan Mode V4
Thermostat Fan State V2	Thermostat Mode V3
Thermostat Operating State V2	Thermostat Setpoint V3
Time Parameters	Time V2
User Code	Version V2
Wake Up V2	