

Z-Wave Protocol Implementation Conformance Statement

Remote Temperature and Humidity Sensor

General Information

Product Identifier:	TH100NX
Brand Name:	Nexia
Product Version:	HW: 2 FW: 1.47
Z-Wave Certification #:	ZC10-17075709

Product Features

Firmware Updatable	Updatable by Consumer by RF
Sensors	Air Temperature Humidity
Battery Quantity	2
Color	White
Battery Type	AAA

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3130
Z-Wave Product Type:	0x5448
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Remote Temperature and Humidity Sensor

Association Group Information

Group # / Max **Description**

Nodes

1 / 1	Z-Wave Plus Lifeline: COMMAND_CLASS_BATTERY, BATTERY_REPORT COMMAND_CLASS_SENSOR_MULTILEVEL, SENSOR_MULTILEVEL_REPORT COMMAND_CLASS_DEVICE_RESET_LOCALLY, DEVICE_RESET_LOCALLY_NOTIFICATION
2 / 5	Temperature reports from: COMMAND_CLASS_SENSOR_MULTILEVEL, SENSOR_MULTILEVEL_REPORT
3 / 5	Humidity reports from: COMMAND_CLASS_SENSOR_MULTILEVEL, SENSOR_MULTILEVEL_REPORT
4 / 5	Temperature driven BASIC_SETs from: COMMAND_CLASS_BASIC, BASIC_SET

Supported Command Classes (12):

COMMAND_CLASS_BASIC, BASIC_SET

6 / 5	Association Group Info	Association V2
	Battery	Configuration
	Device Reset Locally	Firmware Update Meta-Data V2
	Manufacturer Specific V2	Powerlevel
	Sensor Multilevel V5	Version V2
	Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic