

## Z-Wave Protocol Implementation Conformance Statement

# Remote Temperature and Humidity Sensor

### General Information

<b>Product Identifier:</b>	TH100NX
<b>Brand Name:</b>	Nexia
<b>Product Version:</b>	HW: 2 FW: 1.47
<b>Z-Wave Certification #:</b>	ZC10-17075709

### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Sensors</b>	Air Temperature Humidity
<b>Battery Quantity</b>	2
<b>Color</b>	White
<b>Battery Type</b>	AAA

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3130
<b>Z-Wave Product Type:</b>	0x5448
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Remote Temperature and Humidity Sensor

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1	Z-Wave Plus Lifeline: COMMAND_CLASS_BATTERY, BATTERY_REPORT COMMAND_CLASS_SENSOR_MULTILEVEL, SENSOR_MULTILEVEL_REPORT COMMAND_CLASS_DEVICE_RESET_LOCALLY, DEVICE_RESET_LOCALLY_NOTIFICATION
2 / 5	Temperature reports from: COMMAND_CLASS_SENSOR_MULTILEVEL, SENSOR_MULTILEVEL_REPORT
3 / 5	Humidity reports from: COMMAND_CLASS_SENSOR_MULTILEVEL, SENSOR_MULTILEVEL_REPORT
4 / 5	Temperature driven BASIC_SETs from: COMMAND_CLASS_BASIC, BASIC_SET

**Supported Command Classes (12):**

COMMAND\_CLASS\_BASIC, BASIC\_SET

6 / 5	Association Group Info	Association V2
	Battery	Configuration
	Device Reset Locally	Firmware Update Meta-Data V2
	Manufacturer Specific V2	Powerlevel
	Sensor Multilevel V5	Version V2
	Wake Up V2	Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic