

Z-Wave Protocol Implementation Conformance Statement

Flood Sensor

General Information

| | |
|--------------------------------|----------------------|
| Product Identifier: | MT02756 |
| Brand Name: | devolo |
| Product Version: | HW: 1 FW: 1.08:01.05 |
| Z-Wave Certification #: | ZC10-17035462 |

Product Features

| | |
|-------------------------------------|-------------|
| Battery Type | CR123A |
| Battery Quantity | 1 |
| Supported Notification Types | Water Alarm |
| Color | White |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | No |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|--|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x0021 |
| Z-Wave Product Type: | 0x0002 |
| Z-Wave Hardware Platform: | SD3502 |
| Z-Wave Development Kit Version: | 6.51.06 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Notification Sensor / Reporting Sleeping Slave |

Association Group Information

| Group # / Max | Description |
|---------------|-------------|
|---------------|-------------|

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Flood Sensor

2 / 8 The group 2 is for the light control, the device will send the “Basic Set” command to this group.

Supported Command Classes (15):

| | |
|--------------------------|------------------------------|
| Association Group Info | Association V2 |
| Battery | Configuration |
| Device Reset Locally | Firmware Update Meta-Data V2 |
| Manufacturer Specific V2 | Multi-Command |
| Notification V4 | Powerlevel |
| Security S0 | Sensor Binary V2 |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

Basic