

## Z-Wave Protocol Implementation Conformance Statement

### WallMote

#### General Information

<b>Product Identifier:</b>	ZW129-A
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 129 FW: 1.05
<b>Z-Wave Certification #:</b>	ZC10-17025439

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0081
<b>Z-Wave Product Type:</b>	0x0102
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.61.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Portable Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 1	Z-Wave Plus Lifeline. When touching the Button 1 to 2, the Central Scene Notification command will be sent to the associated node (1) in Association group 1.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## WallMote

- 3 / 5            When touching the Button 1, the Multilevel Switch Set command will be sent to the associated nodes in Association group 3.
- 4 / 5            When touching the Button 2, the Basic Set command will be sent to the associated nodes in Association group 4.
- 5 / 5            When touching the Button 2, the Multilevel Switch Set command will be sent to the associated nodes in Association group 5.

### Supported Command Classes (16):

Association Group Info	Association V2
Battery	Central Scene V2
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Notification V4	Powerlevel
Security S0	Version V2
Wake Up V2	Z-Wave Plus Info V2

### Controlled Command Classes (3):

Basic	Switch Binary V2
Switch Multilevel V4	