

## Z-Wave Protocol Implementation Conformance Statement

### WallMote

#### General Information

<b>Product Identifier:</b>	ZW129-A
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 129 FW: 1.05
<b>Z-Wave Certification #:</b>	ZC10-17025439

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0081
<b>Z-Wave Product Type:</b>	0x0102
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.61.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Portable Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 1	Z-Wave Plus Lifeline. When touching the Button 1 to 2, the Central Scene Notification command will be sent to the associated node (1) in Association group 1.

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### WallMote

- 3 / 5            When touching the Button 1, the Multilevel Switch Set command will be sent to the associated nodes in Association group 3.
- 4 / 5            When touching the Button 2, the Basic Set command will be sent to the associated nodes in Association group 4.
- 5 / 5            When touching the Button 2, the Multilevel Switch Set command will be sent to the associated nodes in Association group 5.

### Supported Command Classes (16):

- |                              |                          |
|------------------------------|--------------------------|
| Association Group Info       | Association V2           |
| Battery                      | Central Scene V2         |
| Configuration                | Device Reset Locally     |
| Firmware Update Meta-Data V2 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Multi-Channel V4         |
| Notification V4              | Powerlevel               |
| Security S0                  | Version V2               |
| Wake Up V2                   | Z-Wave Plus Info V2      |

### Controlled Command Classes (3):

- |                      |                  |
|----------------------|------------------|
| Basic                | Switch Binary V2 |
| Switch Multilevel V4 |                  |