

## Z-Wave Protocol Implementation Conformance Statement

### Smart home camera gateway

#### General Information

<b>Product Identifier:</b>	IC731z
<b>Brand Name:</b>	Starvedia
<b>Product Version:</b>	HW: 0 FW: 4.38:03.00:07.00:18.00
<b>Z-Wave Certification #:</b>	ZC10-17035497

#### Product Features

<b>Switch Load Capacity Current</b>	1.5
<b>Firmware Updatable</b>	Updatable by Consumer via Internet
<b>Communications Protocol</b>	Manufacturer Proprietary Protocol
<b>Switch Load Capacity Volt-Ampere</b>	5
<b>Communications Connections</b>	Ethernet (Wired) Ethernet (Wireless/WiFi)
<b>Switch Load Capacity Watts</b>	7.5

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5304
<b>Z-Wave Development Kit Version:</b>	6.51.09

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart home camera gateway

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1                    Z-Wave Plus Lifeline, report Device Reset Locally when reset.

**Supported Command Classes (10):**

Application Status	Association Group Info
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific V2
Powerlevel	Security S0
Version V2	Z-Wave Plus Info V2

**Controlled Command Classes (18):**

Association V2	Basic
Battery	CRC16 Encapsulation
Door Lock	Manufacturer Specific V2
Meter	Multi-Channel Association V3
Multi-Channel V4	Notification V4
Security S0	Sensor Binary V2
Sensor Multilevel	Switch Binary
Switch Color	Switch Multilevel
Version V2	Wake Up V2