

Z-Wave Protocol Implementation Conformance Statement

Garage Door Controller Gen5

General Information

| | |
|--------------------------------|------------------|
| Product Identifier: | ZW062-A |
| Brand Name: | Aeotec |
| Product Version: | HW: 62 FW: 11.11 |
| Z-Wave Certification #: | ZC10-17085731 |

Product Features

| | |
|-------------------------------------|-----------------------------|
| Firmware Updatable | Updatable by Consumer by RF |
| Supported Notification Types | Access Control |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|------------------------------------|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x003E |
| Z-Wave Product Type: | 0x0103 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.51.06 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Barrier Operator / Always On Slave |

Association Group Information

| Group # / Max | Description |
|----------------------|---|
| Nodes | |
| 1 / 5 | Z-Wave Plus Lifeline The Hail CC, Barrier operator report CC can be sent to the associated nodes in this group. |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Garage Door Controller Gen5

Supported Command Classes (15):

| | |
|--------------------------|------------------------------|
| Application Status | Association Group Info |
| Association V2 | Barrier Operator |
| Basic | Configuration |
| Device Reset Locally | Firmware Update Meta-Data V2 |
| Manufacturer Specific V2 | Notification V4 |
| Powerlevel | Security S0 |
| Switch Binary | Version V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (3):

| | |
|---------------|------|
| Basic | Hail |
| Switch Binary | |