



## Z-Wave Protocol Implementation Conformance Statement

### ID Lock 101

#### General Information

<b>Product Identifier:</b>	ID-101
<b>Brand Name:</b>	ID Lock
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-17055585

#### Product Features

<b>Door Lock Type</b>	Deadbolt Motor Attachment
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>IP (Ingress Protection) Rated</b>	Yes
<b>Outdoor Use</b>	Yes
<b>Sensors</b>	Air Temperature Open/Closed (Binary) RF Signal Strength Voltage
<b>Supported Notification Types</b>	Access Control
<b>Battery Quantity</b>	4x or 8x
<b>Battery Type</b>	AA

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## ID Lock 101

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0030
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Door Lock - Keypad / Listening Sleeping Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                Z-Wave Plus Lifeline

**Supported Command Classes (14):**

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Door Lock V2
Firmware Update Meta-Data V2	Manufacturer Specific V2
Notification V4	Powerlevel
Security S0	User Code
Version V2	Z-Wave Plus Info V2