

Z-Wave Protocol Implementation Conformance Statement

Mote

General Information

Product Identifier:	FT130-B
Brand Name:	Oomi
Product Version:	HW: 130 FW: 1.07
Z-Wave Certification #:	ZC10-17045534

Product Features

Z-Wave Scene Type	Central Scene
Firmware Updatable	Updatable by Consumer by RF
Supported Notification Types	Power Management

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x0082
Z-Wave Product Type:	0x0202
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.61.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Wall Controller / Portable Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Mote

- 2 / 5 When touching the Button 1, the Basic Set command will be sent to the associated nodes in Association group 2.
- 3 / 5 When touching the Button 1, the Multilevel Switch Set command will be sent to the associated nodes in Association group 3.
- 4 / 5 When touching the Button 2, the Basic Set command will be sent to the associated nodes in Association group 4.
- 5 / 5 When touching the Button 2, the Multilevel Switch Set command will be sent to the associated nodes in Association group 5.
- 6 / 5 When touching the Button 3, the Basic Set command will be sent to the associated nodes in Association group 6.
- 7 / 5 When touching the Button 3, the Multilevel Switch Set command will be sent to the associated nodes in Association group 7.
- 8 / 5 When touching the Button 4, the Basic Set command will be sent to the associated nodes in Association group 8.
- 9 / 5 When touching the Button 4, the Multilevel Switch Set command will be sent to the associated nodes in Association group 9.

Supported Command Classes (16):

Association Group Info	Association V2
Battery	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Notification V4	Powerlevel
Security S0	Version V2
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (3):

Basic	Switch Binary V2
Switch Multilevel V4	