

## Z-Wave Protocol Implementation Conformance Statement

### Zipato 4 in 1 Door Sensor

#### General Information

<b>Product Identifier:</b>	vs-zd2301.eu
<b>Brand Name:</b>	Zipato
<b>Product Version:</b>	HW: 2 FW: 6.01:10.01
<b>Z-Wave Certification #:</b>	ZC10-17055583

#### Product Features

<b>Battery Type</b>	CR14250
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Sensors</b>	Air Temperature Humidity Luminance
<b>Supported Notification Types</b>	Access Control Home Security

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1F20
<b>Z-Wave Product Type:</b>	0x201F
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Zipato 4 in 1 Door Sensor

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline

**Supported Command Classes (14):**

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Notification V4
Powerlevel	Security S0
Sensor Multilevel V7	Version V2
Wake Up V2	Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic