

## Z-Wave Protocol Implementation Conformance Statement

### In-wall Smart Switch

#### General Information

<b>Product Identifier:</b>	ZW30
<b>Brand Name:</b>	EVA LOGIK
<b>Product Version:</b>	HW: 1 FW: 20.15
<b>Z-Wave Certification #:</b>	ZC10-17045549

#### Product Features

<b>Electric Load Type</b>	Dimmable LED Fluorescent Incandescent LED
<b>Firmware Updatable</b>	Not Updatable
<b>Color</b>	White
<b>IP (Ingress Protection) Rated</b>	No
<b>Switch Load Capacity Current</b>	15
<b>Switch Load Capacity Watts</b>	1800
<b>Neutral Wire Required</b>	Yes
<b>Switch Type</b>	Decorator Paddle Rocker

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-wall Smart Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x1E1C
<b>Z-Wave Product Type:</b>	0xB111
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                Z-Wave Plus Lifeline

**Supported Command Classes (10):**

Association Group Info	Association V2
Basic	Device Reset Locally
Manufacturer Specific V2	Powerlevel
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2