

## Z-Wave Protocol Implementation Conformance Statement

### Smart Plug-In Module (1 Channel)

#### General Information

<b>Product Identifier:</b>	NZW36
<b>Brand Name:</b>	Inovelli
<b>Product Version:</b>	HW: 0 FW: 20.15
<b>Z-Wave Certification #:</b>	ZC10-17045561

#### Product Features

<b>Switch Load Capacity Current</b>	10
<b>Neutral Wire Required</b>	Yes
<b>Switch Type</b>	Push Button
<b>Color</b>	White
<b>IP (Ingress Protection) Rated</b>	No
<b>Firmware Updatable</b>	Updatable by Professional/Technician
<b>Switch Load Capacity Watts</b>	1200
<b>Electric Load Type</b>	Fluorescent Incandescent LED

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Plug-In Module (1 Channel)

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x241C
<b>Z-Wave Product Type:</b>	0xB211
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                The association group supports five nodes and lifeline function

**Supported Command Classes (9):**

Association Group Info	Association V2
Basic	Device Reset Locally
Manufacturer Specific V2	Powerlevel
Switch Binary	Version V2
Z-Wave Plus Info V2	