

Z-Wave Protocol Implementation Conformance Statement

Color Strip

General Information

Product Identifier:	FT121-B
Brand Name:	Oomi
Product Version:	HW: 121 FW: 1.01
Z-Wave Certification #:	ZC10-17045545

Product Features

Firmware Updatable	Updatable by Consumer by RF
Switch Type	Push Button Illuminated
Z-Wave Scene Type	Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x0079
Z-Wave Product Type:	0x0203
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max Nodes	Description
------------------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Color Strip

2 / 5 In this group, the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands would be sent to the associated nodes in association group 2 when the LED Strip receives the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands from the main controller.

Controlled Command Classes (2):

Basic

Hail