

Z-Wave Protocol Implementation Conformance Statement

SmartCode 10 Touchpad Electronic Deadbolt

General Information

Product Identifier:	GED1800
Brand Name:	Weiser
Product Version:	HW: 4 FW: 4.10:64.13
Z-Wave Certification #:	ZC10-17045552

Product Features

Battery Quantity	4
Battery Type	AA
Communications Protocol	Z-Wave Serial API
Door Lock Type	Deadbolt
Firmware Updatable	Updatable by Consumer by RF
Supported Notification Types	Access Control Home Security Power Management

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

SmartCode 10 Touchpad Electronic Deadbolt

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0440
Z-Wave Product Type:	0x0006
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.08
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Door Lock - Keypad / Listening Sleeping Slave

Association Group Information

Group # / Max Description

Nodes

1 / 1	Z-Wave Plus Lifeline Supports the following types of unsolicited messages: Battery Report - sends periodic battery reports containing the battery percentage. Door Lock Operation Report - upon power up, this message will be sent to allow the controller to sync up with the current lock status. Notification Report - many notification types will be sent for status and alarms. The following notification types are supported: Access Control (V2), Home Security (V2), and Power Management (V2). Device Reset Locally Notification - this message will be sent to notify the smart home controller that the lock is resetting back to factory defaults and will be leaving the network.
2 / 5	This group will provide all Notification reports as described for the Lifeline. This group allows other controllers, other than the lifeline, to receive these types of unsolicited messages as well.

Supported Command Classes (18):

Anti-Theft V2	Association Group Info
Association V2	Battery
Configuration	Device Reset Locally
Door Lock Logging	Door Lock V2
Firmware Update Meta-Data V3	Manufacturer Specific V2
Notification V4	Powerlevel
Schedule Entry Lock V2	Security S0
Time Parameters	User Code
Version V2	Z-Wave Plus Info V2