

## Z-Wave Protocol Implementation Conformance Statement

### Smart Plug-In Module (2 Channel)

#### General Information

<b>Product Identifier:</b>	NZW37
<b>Brand Name:</b>	Inovelli
<b>Product Version:</b>	HW: 0 FW: 20.15
<b>Z-Wave Certification #:</b>	ZC10-17055581

#### Product Features

<b>Firmware Updatable</b>	Updatable by Professional/Technician
<b>Electric Load Type</b>	ELV (Electronic)
<b>Switch Load Capacity Current</b>	16 Amps Total (10 Amps Max per Outlet)
<b>Switch Type</b>	Push Button Illuminated

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x241C
<b>Z-Wave Product Type:</b>	0xB211
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Plug-In Module (2 Channel)

### Supported Command Classes (9):

Association Group Info

Basic

Manufacturer Specific V2

Switch Binary

Z-Wave Plus Info V2

Association V2

Device Reset Locally

Powerlevel

Version V2