

## Z-Wave Protocol Implementation Conformance Statement

### Z-Wave Rain Sensor

#### General Information

<b>Product Identifier:</b>	700168
<b>Brand Name:</b>	Popp
<b>Product Version:</b>	HW: 1 FW: 1.02
<b>Z-Wave Certification #:</b>	ZC10-17065642

#### Product Features

<b>Firmware Updatable</b>	Not Updatable
<b>Sensors</b>	Rain Rate
<b>Supported Meter Type</b>	Water
<b>Color</b>	Dark Gray
<b>Battery Type</b>	AAA
<b>Battery Quantity</b>	2

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0011
<b>Z-Wave Product Type:</b>	0x0004
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Rain Sensor

### Association Group Information

**Group # / Max    Description**

**Nodes**

- 1 / 5            Z-Wave Plus Lifeline
- 2 / 5            Switching Command when Rain (> 0 mm/h). Basic Set Command is sent.
- 3 / 5            Heavy Rain detected. Basic Set Command is sent.

**Supported Command Classes (13):**

- |                          |                              |
|--------------------------|------------------------------|
| Association Group Info   | Association V2               |
| Battery                  | Configuration                |
| Device Reset Locally     | Firmware Update Meta-Data V3 |
| Manufacturer Specific V2 | Meter V4                     |
| Powerlevel               | Sensor Multilevel V7         |
| Version V2               | Wake Up V2                   |
| Z-Wave Plus Info V2      |                              |

**Controlled Command Classes (1):**

- Basic