

## Z-Wave Protocol Implementation Conformance Statement

### Indoor Siren, Multisound, Z-wave

#### General Information

<b>Product Identifier:</b>	ph-pse02.eu
<b>Brand Name:</b>	Zipato
<b>Product Version:</b>	HW: 1 FW: 1.15:01.12
<b>Z-Wave Certification #:</b>	ZC10-17055596

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Supported Notification Types</b>	Home Security

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x000A
<b>Z-Wave Product Type:</b>	0x0004
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Siren / Always On Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Indoor Siren, Multisound, Z-wave

### Supported Command Classes (14):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Notification V4
Powerlevel	Security S0
Sensor Binary V2	Switch Binary
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Notification V4