

Z-Wave Protocol Implementation Conformance Statement

Smart dimmer

General Information

Product Identifier:	FX-D67A
Brand Name:	FLEX AUTOMATION
Product Version:	HW: 1 FW: 2.00
Z-Wave Certification #:	ZC10-17055611

Product Features

Color	White
Electric Load Type	Incandescent
Firmware Updatable	Updatable by Professional/Technician
Switch Load Capacity Watts	300w
Switch Type	Push Button

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Brazil
Z-Wave Product ID:	0x0008
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart dimmer

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 This dimmer plug in switch can be associated by 5 devices

Supported Command Classes (12):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Powerlevel
Switch All	Switch Multilevel
Version V2	Z-Wave Plus Info V2