

## Z-Wave Protocol Implementation Conformance Statement

### Scout Hub 1S

#### General Information

<b>Product Identifier:</b>	SCHUB02
<b>Brand Name:</b>	Scout Alarm
<b>Product Version:</b>	HW: 1 FW: 2.05:01.21
<b>Z-Wave Certification #:</b>	ZC10-17075684

#### Product Features

<b>Communications Connections</b>	Ethernet (Wired)
<b>Firmware Updatable</b>	Updatable by Consumer by Wire
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3032
<b>Z-Wave Product Type:</b>	0x4882
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Static Controller
<b>Z-Wave Device Type / Role Type:</b>	Central Controller / Central Static Controller

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Scout Hub 1S

### Supported Command Classes (10):

Application Status	Association Group Info
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific V2
Powerlevel	Security S0
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (13):

Association Group Info	Association V2
Basic	CRC16 Encapsulation
Device Reset Locally	Door Lock
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Channel V4	Security S0
Switch Multilevel	User Code
Wake Up V2	