

## Z-Wave Protocol Implementation Conformance Statement

### In-Wall Smart Switch

#### General Information

<b>Product Identifier:</b>	14291/ZW4005
<b>Brand Name:</b>	GE
<b>Product Version:</b>	HW: 255 FW: 5.21:05.21
<b>Z-Wave Certification #:</b>	ZC10-17075672

#### Product Features

<b>Neutral Wire Required</b>	Yes
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Type</b>	Decorator Paddle Rocker

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3036
<b>Z-Wave Product Type:</b>	0x4952
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.10
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
Nodes	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall Smart Switch

- 2 / 5 Supports Basic Set and is controlled with the local load.
- 3 / 5 Supports Basic Set and is controlled by double pressing the On or Off button.

### Supported Command Classes (15):

Association Group Info	Association V2
Basic	Configuration
CRC16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Powerlevel	Scene Activation
Scene Actuator Conf	Switch All
Switch Binary	Version V2
Z-Wave Plus Info V2	

### Controlled Command Classes (1):

Basic