



Z-Wave Protocol Implementation Conformance Statement

Smart Switch 6

General Information

| | |
|--------------------------------|-----------------|
| Product Identifier: | ZW096-D07 |
| Brand Name: | Aeotec |
| Product Version: | HW: 96 FW: 1.00 |
| Z-Wave Certification #: | ZC10-17075674 |

Product Features

| | |
|-----------------------------|--|
| Electric Load Type | Dimmable LED ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic) |
| Firmware Updatable | Updatable by Consumer by RF |
| Supported Meter Type | Electric Energy |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Switch 6

Z-Wave Technical Information

| | |
|--|---------------------------------------|
| Z-Wave Frequency: | Hong Kong |
| Z-Wave Product ID: | 0x0060 |
| Z-Wave Product Type: | 0x0303 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.51.05 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | On/Off Power Switch / Always On Slave |

Association Group Information

| Group # / Max | Description |
|----------------------|--------------------|
|----------------------|--------------------|

Nodes

| | |
|-------|--|
| 1 / 5 | Z-Wave Plus Lifeline. The Hial CC and Basic Report CC (configured by parameter 80) can be sent to the associated nodes in this group. |
| 2 / 5 | Forward the Basic Set, Switch Binary Set to associated nodes in Group 2 when the Plug receives the Basic Set, Switch Binary Set commands from the main controller. |

Supported Command Classes (17):

| | |
|------------------------------|--------------------------|
| Association Group Info | Association V2 |
| Basic | Clock |
| Configuration | Device Reset Locally |
| Firmware Update Meta-Data V2 | Manufacturer Specific V2 |
| Meter V3 | Powerlevel |
| Security S0 | Switch All |
| Switch Binary | Switch Color |
| Switch Multilevel V3 | Version V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (3):

| | |
|---------------|------|
| Basic | Hail |
| Switch Binary | |