

## Z-Wave Protocol Implementation Conformance Statement

### Smart Color Button

#### General Information

**Product Identifier:** PSR04  
**Brand Name:** Philio  
**Product Version:** HW: 1 FW: 1.09:01.06  
**Z-Wave Certification #:** ZC10-17105808

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? No  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? Yes  
Supports Security S2? No  
SmartStart Compatible? No

#### Z-Wave Technical Information

**Z-Wave Frequency:** Brazil  
**Z-Wave Product ID:** 0x0022  
**Z-Wave Product Type:** 0x0009  
**Z-Wave Hardware Platform:** SD3502  
**Z-Wave Development Kit Version:** 6.51.09  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Wall Controller / Portable Slave

#### Association Group Information

**Group # / Max**    **Description**

##### Nodes

1 / 8            Z-Wave Plus Lifeline. The group 1 is for receiving the report message, like triggered event, temperature, humidity etc.  
2 / 8            Lighting control group

##### Supported Command Classes (14):

Association Group Info	Association V2
Battery	Central Scene
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Multi-Command	Powerlevel

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Color Button

### Controlled Command Classes (2):

Basic

Central Scene