

## Z-Wave Protocol Implementation Conformance Statement

### Wi-Fi Gateway

#### General Information

<b>Product Identifier:</b>	HSI01(KTS32)
<b>Brand Name:</b>	KDDI CORPORATION
<b>Product Version:</b>	HW: 1 FW: 0.00:01.07
<b>Z-Wave Certification #:</b>	ZC10-17105799

#### Product Features

<b>Color</b>	White
<b>Communications Protocol</b>	Z-Wave Serial API
<b>Firmware Updatable</b>	Updatable by Manufacturer
<b>Gateway Has Preferred Partners</b>	No
<b>Sensors</b>	Air Temperature Humidity Luminance Motion/No Motion (Binary) Open/Closed (Binary)
<b>Supported Notification Types</b>	Home Security

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Wi-Fi Gateway

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Japan
<b>Z-Wave Product ID:</b>	0x0004
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5304
<b>Z-Wave Development Kit Version:</b>	6.51.10
<b>Z-Wave Library Type:</b>	Static Controller
<b>Z-Wave Device Type / Role Type:</b>	Central Controller / Central Static Controller

### Association Group Information

**Group # / Max**    **Description**

#### Nodes

1 / 16            Z-Wave Plus Lifeline; A NOTIFICATION frame is sent to the nodes in this association group when Lifeline event occurs.

#### Supported Command Classes (10):

Application Status	Association Group Information V3
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific
Powerlevel	Security S0
Version V2	Z-Wave Plus Info V2

#### Controlled Command Classes (16):

Association Group Information V3	Association V2
Basic	Battery
Configuration	CRC16 Encapsulation
Meter V4	Multi-Channel Association V3
Multi-Channel V4	Notification V5
Security S0	Sensor Binary V2
Sensor Multilevel V7	Switch Binary
Version V2	Wake Up V2