



Z-Wave Protocol Implementation Conformance Statement

Bulb

General Information

Product Identifier: FT098-K55
Brand Name: Oomi
Product Version: HW: 98 FW: 1.07
Z-Wave Certification #: ZC10-17095780

Product Features

Firmware Updatable Updatable by Consumer by RF
Switch Type Toggle
Z-Wave Scene Type Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: China
Z-Wave Product ID: 0x0062
Z-Wave Product Type: 0x1D03
Z-Wave Hardware Platform: ZM5101
Z-Wave Development Kit Version: 6.51.09
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Light Dimmer Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Bulb

Association Group Information

Group # / Max **Description**

Nodes

- | | |
|-------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1 / 5 | The association group 1 is the Z-Wave Lifeline group. The Hail CC and Basic Report CC (configurable) can be sent to the associated nodes in association group 1. |
| 2 / 5 | In this group, the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands would be sent to the associated nodes in association group 2 when the Bulb receives the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands from the main controller. |

Supported Command Classes (16):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S0	Switch All
Switch Color	Switch Multilevel V2
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (2):

Basic	Hail
-------	------