

Z-Wave Protocol Implementation Conformance Statement

Siren

General Information

Product Identifier:	WK-0004
Brand Name:	WINKA SYSIT
Product Version:	HW: 16 FW: 1.50
Z-Wave Certification #:	ZC10-17105814

Product Features

Supported Notification Types	Siren
-------------------------------------	-------

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1DB1
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Siren / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5	Z-Wave Plus Lifeline. This group supporting command class lists as below: COMMAND_CLASS_SWITCH_BINARY, SWITCH_BINARY_REPORT COMMAND_CLASS_NOTIFICATION, NOTIFICATION_REPORT COMMAND_CLASS_DEVICE_RESET_LOCALLY, DEVICE_RESET_LOCALLY_NOTIFICATION
-------	--

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Siren

- 3 / 5 This group is for power management notification report. when the power source is changed, siren will send a notification report to nodes associated in group 3. This group supporting command class lists as below:
COMMAND_CLASS_NOTIFICATION NOTIFICATION_REPORT
- 4 / 5 This group is for Siren status report. When siren is activated or inactivated, it will send a notification report to nodes associated in group This group supporting command class lists as below:
COMMAND_CLASS_NOTIFICATION NOTIFICATION_REPORT
- 5 / 5 This group is for binary switch status report. When siren is activated or inactivated, it will send a binary switch report to nodes associated in group This group supporting command class lists as below:
COMMAND_CLASS_SWITCH_BINARY SWITCH_BINARY_REPORT

Supported Command Classes (13):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Indicator
Manufacturer Specific V2	Notification V8
Powerlevel	Security S0
Switch Binary	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic