

## Z-Wave Protocol Implementation Conformance Statement

### Outlet

#### General Information

<b>Product Identifier:</b>	WK-0003
<b>Brand Name:</b>	WINKA SYSIT
<b>Product Version:</b>	HW: 16 FW: 1.36
<b>Z-Wave Certification #:</b>	ZC10-17105819

#### Product Features

<b>Supported Meter Type</b>	Electric Energy
<b>Supported Notification Types</b>	Power Management
<b>Switch Type</b>	Toggle

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1D61
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
Nodes	

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### Outlet

- 2 / 5 Control Group, If over-load is occurred, the device will send BASIC\_SET to nodes associated in group 2.  
Support Command List as Below: COMMAND\_CLASS\_BASIC, BASIC\_SET
- 3 / 5 Power Manager Group. If Over-load is occurred, device will send notification report to nodes associated in group 3. Support List as Below: COMMAND\_CLASS\_NOTIFICATION, POWERMANAGEMENT STATUS (OVER LOAD)

### Supported Command Classes (14):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Manufacturer Specific V2
Meter V4	Notification V8
Powerlevel	Security S0
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic