

## Z-Wave Protocol Implementation Conformance Statement

### Door Contact

#### General Information

<b>Product Identifier:</b>	ZD2112JP-5
<b>Brand Name:</b>	Vision
<b>Product Version:</b>	HW: 5 FW: 23.18
<b>Z-Wave Certification #:</b>	ZC10-17125897

#### Product Features

<b>Battery Quantity</b>	2
<b>Battery Type</b>	AAA
<b>Color</b>	White
<b>Outdoor Use</b>	No
<b>Sensors</b>	Open/Closed (Binary)
<b>Supported Notification Types</b>	Access Control

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Japan
<b>Z-Wave Product ID:</b>	0x01A3
<b>Z-Wave Product Type:</b>	0x2001
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Door Contact

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                \* Group 1 = Lifeline

2 / 5                \* Group 2 = On/Off Control

**Supported Command Classes (15):**

Association Group Info	Association V2
Battery	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Notification V8	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	

**Controlled Command Classes (1):**

Basic