

## Z-Wave Protocol Implementation Conformance Statement

# S100 Master Roller Dimmer iO

### General Information

<b>Product Identifier:</b>	10002021-13X
<b>Brand Name:</b>	Simon
<b>Product Version:</b>	HW: 1 FW: 4.24:79.50
<b>Z-Wave Certification #:</b>	ZC10-18026013

### Product Features

<b>Firmware Updatable</b>	Updatable by Professional/Technician
<b>Neutral Wire Required</b>	Yes
<b>Z-Wave Scene Type</b>	Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0000
<b>Z-Wave Product Type:</b>	0x0008
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Always On Slave

### Association Group Information

Group # / Max	Description
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## S100 Master Roller Dimmer iO

2 / 20 ctrl. This group is used to add the devices to be controlled by Master Roller blind. Device sends Basic Sets and Gets, and Manufacturer specific Gets, Configuration Gets and Sets when manual association is being performed over Simon devices.

### Supported Command Classes (12):

Association Group Information V3	Association V2
Basic	Central Scene V3
Configuration V2	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Powerlevel	Switch Multilevel V3
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (5):

Association V2	Basic
Configuration V2	Manufacturer Specific V2
Switch Multilevel V3	