

## Z-Wave Protocol Implementation Conformance Statement

# Z-Wave Wall Dimmer with RGB LED

### General Information

<b>Product Identifier:</b>	HS-WD200+
<b>Brand Name:</b>	HomeSeer
<b>Product Version:</b>	HW: 255 FW: 5.08
<b>Z-Wave Certification #:</b>	ZC10-18026019

### Product Features

<b>Neutral Wire Required</b>	Yes
<b>Outdoor Use</b>	No
<b>Z-Wave Scene Type</b>	Scene & Central Scene
<b>Electric Load Type</b>	Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) Incandescent
<b>Color</b>	White
<b>Switch Type</b>	Decorator Paddle Rocker
<b>Switch Load Capacity Watts</b>	600 Watts Incandescent
<b>Firmware Updatable</b>	Updatable by Consumer by RF

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Wall Dimmer with RGB LED

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3036
<b>Z-Wave Product Type:</b>	0x4447
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline

**Supported Command Classes (18):**

Association Group Info	Association V2
Basic	Central Scene V3
Configuration V3	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific
Powerlevel	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch All
Switch Multilevel V4	Transport Service V2
Version V2	Z-Wave Plus Info V2

**Controlled Command Classes (2):**

Central Scene V3	Supervision
------------------	-------------