

Z-Wave Protocol Implementation Conformance Statement

Zipato Carbon Monoxide Sensor

General Information

Product Identifier:	hm-hs1ca-z.eu
Brand Name:	Zipato
Product Version:	HW: 255 FW: 1.10
Z-Wave Certification #:	ZC10-17115860

Product Features

Color	White
Supported Notification Types	CO Alarm Home Security
Battery Quantity	1
Battery Type	CR17335

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1000
Z-Wave Product Type:	0x8005
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.08
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Zipato Carbon Monoxide Sensor

Association Group Information

Group # / Max Description

Nodes

- | | |
|-------|--|
| 1 / 1 | Association group 1: Lifeline association group Include command classes: Battery report, Notification report, and Device Reset Locally notification, Binary report. |
| 2 / 5 | Association group 2: Root Device group(Binary Sensor) Binary Sensor Command Class: Compatible with 300 series 1-Binary Sensor reports status of CO or no CO via Lifeline. 2-When the sensor detects status change of CO and no CO, the device will be triggered. |
| 3 / 5 | Association group 3: Root Device group(Notification) 1-Notification reports status of detect CO or no CO via Lifeline. 2-When the sensor detects status change of CO and no CO, the device will be triggered. |

Supported Command Classes (11):

- | | |
|--------------------------|----------------------|
| Association Group Info | Association V2 |
| Battery | Device Reset Locally |
| Manufacturer Specific V2 | Notification V4 |
| Powerlevel | Sensor Binary V2 |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |