

## Z-Wave Protocol Implementation Conformance Statement

# In-Wall Tamper Resistant Smart Outlet

### General Information

<b>Product Identifier:</b>	14288/ZW1002
<b>Brand Name:</b>	GE
<b>Product Version:</b>	HW: 255 FW: 5.24
<b>Z-Wave Certification #:</b>	ZC10-18025987

### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
---------------------------	-----------------------------

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3133
<b>Z-Wave Product Type:</b>	0x4952
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 5	Z-Wave Plus Lifeline
2 / 5	Supports Basic Set and is controlled with the local load
3 / 5	Supports Basic Set and is controlled by pressing the On or Off button

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall Tamper Resistant Smart Outlet

### Supported Command Classes (15):

Association Group Info	Association V2
Basic	Configuration
CRC16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Powerlevel	Scene Activation
Scene Actuator Conf	Switch All
Switch Binary	Version V2
Z-Wave Plus Info V2	

### Controlled Command Classes (1):

Basic