

Z-Wave Protocol Implementation Conformance Statement

PANIC BUTTON

General Information

Product Identifier:	AC136-F
Brand Name:	Everspring
Product Version:	HW: 1 FW: 1.01:00.01
Z-Wave Certification #:	ZC10-18015959

Product Features

Firmware Updatable	Updatable by Consumer via Internet
Battery Type	AAA
Battery Quantity	2
Color	White
Supported Notification Types	Appliance
Switch Type	Push Button

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Japan
Z-Wave Product ID:	0x0002
Z-Wave Product Type:	0x000A
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

PANIC BUTTON

Association Group Information

Group # / Max **Description**

Nodes

1 / 1 Association with 1 node.

2 / 4 Association with 4 nodes (i.e. end devices such as smart plugs and other lighting controllers). This allows the On/Off module to receive commands directly from these end devices without the participation of the controller.

Supported Command Classes (15):

- | | |
|------------------------------|--------------------------|
| Association Group Info | Association V2 |
| Battery | Device Reset Locally |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Notification V4 | Powerlevel |
| Security S0 | Security S2 |
| Supervision | Transport Service V2 |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

- Basic