

Z-Wave Protocol Implementation Conformance Statement

PIR Sensor

General Information

| | |
|--------------------------------|------------------|
| Product Identifier: | ne-nas-pd01zt.eu |
| Brand Name: | Zipato |
| Product Version: | HW: 66 FW: 3.80 |
| Z-Wave Certification #: | ZC10-18015916 |

Product Features

| | |
|-------------------------------------|---------------|
| Battery Type | CR17345 |
| Color | White |
| Sensors | Luminance |
| Supported Notification Types | Home Security |
| Battery Quantity | 1 |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | No |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|--|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x1089 |
| Z-Wave Product Type: | 0x0003 |
| Z-Wave Hardware Platform: | ZM5202 |
| Z-Wave Development Kit Version: | 6.51.06 |
| Z-Wave Library Type: | Routing Slave |
| Z-Wave Device Type / Role Type: | Notification Sensor / Reporting Sleeping Slave |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

PIR Sensor

Association Group Information

Group # / Max **Description**

Nodes

1 / 4 Z-Wave Plus Lifeline

2 / 4 GROUP 2 allows for sending control commands to associated devices such as relay module, lighting, etc.
This association group is configured through the advanced parameters no. 2, 3, 5 and 8. This Group Support:
BASIC_SET

3 / 4 GROUP 3 allows for Send Notification to associated devices in this group. This Group Support:
NOTIFICATION_REPORT_V4

4 / 4 GROUP 4 allows for Send Sensor Binary Report to associated devices in this group. This Group Support:
SENSOR_BINARY_REPORT_V2

Supported Command Classes (13):

| | |
|------------------------|--------------------------|
| Association Group Info | Association V2 |
| Battery | Configuration |
| Device Reset Locally | Manufacturer Specific V2 |
| Notification V4 | Powerlevel |
| Sensor Binary V2 | Sensor Multilevel V7 |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

Basic