

Z-Wave Protocol Implementation Conformance Statement

Color Strip

General Information

Product Identifier:	FT121-K
Brand Name:	Oomi
Product Version:	HW: 121 FW: 1.04
Z-Wave Certification #:	ZC10-18015934

Product Features

Switch Type	Push Button Illuminated
Z-Wave Scene Type	Scene
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	China
Z-Wave Product ID:	0x0079
Z-Wave Product Type:	0x1D03
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.10
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Color Strip

2 / 5 In this group, the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands would be sent to the associated nodes in association group 2 when the LED Strip receives the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands from the main controller.

Supported Command Classes (16):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S0	Switch All
Switch Color	Switch Multilevel V2
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (2):

Basic	Hail
-------	------