

Z-Wave Protocol Implementation Conformance Statement

LED Dimmer

General Information

Product Identifier:	SR-ZV9101FX-US
Brand Name:	Sunricher
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-18015938

Product Features

Firmware Updatable	Updatable by Consumer by RF
Supported Notification Types	System

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xD002
Z-Wave Product Type:	0x0201
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Z-Wave Plus Lifeline

Z-Wave Protocol Implementation Conformance Statement

(Continued)

LED Dimmer

Supported Command Classes (19):

Association Group Information V3

Basic V2

Device Reset Locally

Manufacturer Specific V2

Powerlevel

Scene Actuator Conf

Security S2

Switch Color V3

Transport Service V2

Z-Wave Plus Info V2

Association V2

Configuration V2

Firmware Update Meta-Data V4

Notification V8

Scene Activation

Security S0

Supervision

Switch Multilevel V4

Version V2