

## Z-Wave Protocol Implementation Conformance Statement

# Z-Wave Plus Smart Switch - Single Rocker

### General Information

|                                |                                |
|--------------------------------|--------------------------------|
| <b>Product Identifier:</b>     | SDLS2-ZWAVE5                   |
| <b>Brand Name:</b>             | Ecolink Intelligent Technology |
| <b>Product Version:</b>        | HW: 255 FW: 10.01              |
| <b>Z-Wave Certification #:</b> | ZC10-18015957                  |

### Product Features

|                         |                         |
|-------------------------|-------------------------|
| <b>Battery Quantity</b> | 2                       |
| <b>Color</b>            | White                   |
| <b>Sensors</b>          | Open/Closed (Binary)    |
| <b>Switch Type</b>      | Decorator Paddle Rocker |
| <b>Battery Type</b>     | AA                      |

### Z-Wave Product Information

|                                      |     |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology?  | Yes |
| Supports Z-Wave Network Security?    | Yes |
| Supports Z-Wave AES-128 Security S0? | No  |
| Supports Security S2?                | No  |
| SmartStart Compatible?               | No  |

### Z-Wave Technical Information

|  |  |
|--|--|
| <b>Z-Wave Frequency:</b>               | U.S. / Canada / Mexico                         |
| <b>Z-Wave Product ID:</b>              | 0x0005   |
| <b>Z-Wave Product Type:</b>            | 0x0006   |
| <b>Z-Wave Hardware Platform:</b>       | ZM5202   |
| <b>Z-Wave Development Kit Version:</b> | 6.51.09  |
| <b>Z-Wave Library Type:</b>            | Enhanced Slave                                 |
| <b>Z-Wave Device Type / Role Type:</b> | On/Off Power Switch / Listening Sleeping Slave |

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Plus Smart Switch - Single Rocker

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline

**Supported Command Classes (9):**

|                        |                |
|------------------------|----------------|
| Association Group Info | Association V2 |
| Basic                  | Battery        |
| Manufacturer Specific  | Powerlevel     |
| Switch Binary          | Version V2     |
| Z-Wave Plus Info V2    |                |