

Z-Wave Protocol Implementation Conformance Statement

B.One Smart Sensor

General Information

Product Identifier:	B1SS02-ZW-AU
Brand Name:	B.One
Product Version:	HW: 1 FW: 1.04
Z-Wave Certification #:	ZC10-18025994

Product Features

Battery Quantity	2
Supported Notification Types	Access Control Home Security
Battery Type	AAA
Sensors	Open/Closed (Binary)

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x0201
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.08
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

B.One Smart Sensor

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Door/Window Sensor will send notification report and battery report to the associated nodes.

2 / 5 Sensor will send Basic Set to the associated nodes when the sensor body and magnet removed or combined.

Supported Command Classes (13):

- | | |
|--------------------------|------------------------------|
| Association Group Info | Association V2 |
| Battery | Configuration |
| Device Reset Locally | Firmware Update Meta-Data V2 |
| Manufacturer Specific V2 | Notification V5 |
| Powerlevel | Security S0 |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

Basic