

Z-Wave Protocol Implementation Conformance Statement

EZmultiPli

General Information

Product Identifier:	EZMultiPli
Brand Name:	Express Controls LLC
Product Version:	HW: 3 FW: 2.01
Z-Wave Certification #:	ZC10-18015976

Product Features

Firmware Updatable	Updatable by Consumer by RF
Supported Notification Types	Home Security
Sensors	Air Temperature Luminance Motion/No Motion (Binary)

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0004
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

EZmultiPli

2 / 4

This group is used to directly turn lights on or off when motion is detected. Up to four (4) Z-Wave devices can be associated in this group. EZMultiPli will send a BASIC ON command to all devices that are associated in this group. Note that including the NodeID of EZMultiPli in this group will control the LED which will come on when motion is detected and goes off when no motion has been detected for OnTime minutes.

Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration V3
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Node Naming
Notification V8	Powerlevel
Security S2	Sensor Multilevel V6
Supervision	Switch Color
Switch Multilevel V2	Transport Service V2
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic