

Z-Wave Protocol Implementation Conformance Statement

HC Dimmer FM

General Information

Product Identifier:	MT 02760
Brand Name:	devolo
Product Version:	HW: 4 FW: 3.08:03.10
Z-Wave Certification #:	ZC10-18025988

Product Features

Color	White
Neutral Wire Required	Yes
Sensors	Acceleration Y-Axis Air Temperature
Supported Meter Type	Electric Energy
Supported Notification Types	Power Management

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0051
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

HC Dimmer FM

Association Group Information

Group # / Max Description

Nodes

1 / 5	Z-Wave Plus Lifeline
2 / 16	Basic on/off (triggered at change of the input I1 and reflecting state of the output Q)
3 / 16	Start level change/stop level change (triggered at change of the input I1 state and reflecting its state)
4 / 16	Multilevel set (triggered at changes of state/value of the Flush Dimmer) up to 16 nodes
5 / 16	Basic on/off (triggered at change of the input I2 state and reflecting its state) up to 16 nodes.
6 / 16	Notification report (triggered at change of the input I2 state and reflecting its state)
7 / 16	Binary sensor (triggered at change of the input I2 state and reflecting its state)
8 / 16	Basic on/off (triggered at change of the input I3 state and reflecting its state)
9 / 16	Notification report (triggered at change of the input I3 state and reflecting its state)
10 / 16	Binary sensor report (triggered at change of the input I3 state and reflecting its state)
11 / 16	Multilevel sensor report (triggered at change of temperature sensor)

Supported Command Classes (19):

Association Group Information V2	Association V2
Basic	Configuration
Device Reset Locally	Manufacturer Specific V2
Meter V4	Multi-Channel Association V3
Multi-Channel V4	Notification V5
Powerlevel	Security S0
Sensor Binary	Sensor Multilevel V7
Switch All	Switch Binary
Switch Multilevel V3	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (2):

Basic	Switch Multilevel V3
-------	----------------------