

## Z-Wave Protocol Implementation Conformance Statement

### LED Bulb 6: Multi-White

#### General Information

Product Identifier:	ZWA001-C
Brand Name:	Aeotec
Product Version:	HW: 1 FW: 1.10
Z-Wave Certification #:	ZC10-18036060

#### Product Features

Color	White
Firmware Updatable	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
Nodes	
1 / 1	LED Bulb will send its status to the lifeline group when the state of the LED Bulb is changed. 1). Set Configuration parameter 0x50 to 0: nothing 2). Set Configuration parameter 0x50 to 1: Sending Basic Report

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## LED Bulb 6: Multi-White

### Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S0	Security S2
Supervision	Switch Color V2
Switch Multilevel V2	Transport Service V2
Version V2	Z-Wave Plus Info V2