

## Z-Wave Protocol Implementation Conformance Statement

### Z-WAVE AC MASTER

#### General Information

<b>Product Identifier:</b>	ZXT-600JP
<b>Brand Name:</b>	ECO LIFE ENGINEERING
<b>Product Version:</b>	HW: 3 FW: 1.03:01.07:171.06
<b>Z-Wave Certification #:</b>	ZC10-18036053

#### Product Features

<b>Battery Quantity</b>	2
<b>Thermostat HVAC Systems Supported</b>	(No feature option values set for this feature)
<b>Thermostat Modes</b>	Auto Away Cool Dry Air Fan Only Heat Resume
<b>Battery Type</b>	AA
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Sensors</b>	Target Temperature

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-WAVE AC MASTER

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Japan
<b>Z-Wave Product ID:</b>	0x8490
<b>Z-Wave Product Type:</b>	0x0109
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.61.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Thermostat - HVAC / Listening Sleeping Slave

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1            Association Group #1 (max. 1 node) is default to associate with the primary controller (Gateway/Hub/Controller) for AC Master Status change report, refer to below for report details: a) Current Room Temperature (report in precision of 0.5°C or 1°F) (It will be according to Configuration Parameter 39 setting to decide the trigger level) b) Current Battery Level (Only apply in Low Battery Warning happened) c) Device Reset Locally Notification (Only report when the AC Master has been triggered the RESET TO DEFAULT)

**Supported Command Classes (17):**

Application Status	Association Group Information V3
Association V2	Basic
Battery	Configuration V2
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Powerlevel
Security S0	Sensor Multilevel V7
Thermostat Fan Mode V4	Thermostat Mode V3
Thermostat Setpoint V3	Version V2
Z-Wave Plus Info V2	