

Z-Wave Protocol Implementation Conformance Statement

LED Bulb 6:Multi-Colour

General Information

| | |
|-------------------------|----------------|
| Product Identifier: | ZWA002-C |
| Brand Name: | Aeotec |
| Product Version: | HW: 1 FW: 1.19 |
| Z-Wave Certification #: | ZC10-18046097 |

Product Features

| | |
|----------------------------|-----------------------------|
| Color | White |
| Firmware Updatable | Updatable by Consumer by RF |
| Switch Load Capacity Watts | 10 |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|---------------------------------|---------------------------------------|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x0002 |
| Z-Wave Product Type: | 0x0003 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.51.09 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Light Dimmer Switch / Always On Slave |

Association Group Information

| Group # / Max Nodes | Description |
|---------------------|-------------|
|---------------------|-------------|

Z-Wave Protocol Implementation Conformance Statement

(Continued)

LED Bulb 6:Multi-Colour

Supported Command Classes (14):

Association Group Info
Basic
Device Reset Locally
Manufacturer Specific V2
Security S0
Switch Color
Version V2

Association V2
Configuration
Firmware Update Meta-Data V2
Powerlevel
Switch All
Switch Multilevel V2
Z-Wave Plus Info V2